

## SRR Remote Control

*The homeowner's  
easy-to-use  
remote control  
at an easy-to-  
handle price*



Transmitter



Receiver

**H**ow does Hunter make their already easy-to-use residential controllers even easier to use? With the industry's most convenient and economical remote crafted specifically for residential use. Nothing else makes it easier for a homeowner to operate their automatic irrigation system. With the SRR, the power to control your landscape's watering is right in your hands. This handy accessory makes it possible for you to operate your system without having to walk to (and manually operate) the controller. And, considering many

homes have their controller located inside the garage, by using the SRR, you can access your system without the inconvenience of pulling up that big door and working your way around parked cars and stored items. Best of all, you'll find that the SRR offers features that other remotes don't—including sturdy ABS construction, large LCD display and 4-button operation, 8 different run-time settings, and a transmission range up to 450 feet—all at a price that can't be beat.

### Features & Benefits



#### Remote operation of any station or program

Signal transmits up to 450 feet away

#### 128 different programmable security codes

Allows multiple SRR systems to be used in the same area

#### Operates on one 9V battery for up to a year

Automatic shutoff extends battery life when not in use

#### Variable remote-activated station run times

Allows a one-time change in duration without affecting regular program

#### Weather-resistant connection port

Allows temporary outdoor connection of remote receiver

## Models

SRR-KIT – Transmitter, receiver, wiring harness, and owner's manual

SRR-SCWH – Connection Kit with 25' shielded cable

SRR-TR – Transmitter

SRR-R – Receiver

## Dimensions

- Transmitter: 4¾" H x 2½" W x 1¼" D (12 cm H x 6 cm W x 3 cm D)
- Receiver: 4¾" H x 2½" W x 1" D (12 cm H x 6 cm W x 2.5 cm D)

## Specifications and Features

- Address range: 0 to 127
- Maximum stations supported: 48
- Run times: Eight settings from 1 to 30 min
- Range: Up to 450' (137 m) line of sight
- Transmitter: 9V alkaline battery (not included)
- Receiver: 24VAC, 0.01 Amps from controller
- System Operating Frequency: 315 MHz
- Install SmartPort® up to 50' from controller (use shielded cable wiring harness)
- No FCC license required



## Homeowners: Simple and Reliable Just Got Simpler

*Ideally, you want the job of keeping your landscape green to be as easy as it can be. Well, Hunter's SRR remote was created to do precisely that. With this handy tool, you'll be able to activate zones with your Hunter controller from anywhere in your yard. Ask your contractor for all the details on this valuable upgrade.*



## Easy Indoor or Outdoor Installation



▲ Typical indoor installation of SRR receiver unit.



▲ Outdoor mounting of the SRR SmartPort® allows instant access to the controller and eliminates the need to enter the building.



▲ Port can be mounted up to 50 feet from controller with use of shielded cable wiring harness.

## SPECIFICATION GUIDE

EXAMPLE: **SRR - KIT**

MODEL	FEATURES
SRR	KIT = Transmitter, Receiver and Wiring Harness SCWH = 25' Shielded Cable Connection Kit TR = Transmitter R = Receiver